

Reduce your stock holdings and down time today

6 - 32 VOLT LED PILOT LIGHTS

The PowerLight™ Multi Voltage LED Pilot Lights have been designed to consolidate all No Load LED's under four easy to use part numbers.

With an operating range of 6 – 32 volts DC, these units have been specifically designed to operate in the harshest conditions. They are compact in design and are highly resistant to vibration, dust and moisture.

Their reliability helps to eliminate costly downtime caused by the regular replacement of standard incandescent globes, often used as indicators. LED pilot lights are far more tolerant to changes in voltage and voltage spikes.

Please Note: If a loaded LED Pilot Light is required (for alternator excitation) a resistor assembly needs to be applied across the power and ground.

Features

- Operating Range: 6 – 32 Volts DC
- Current Draw: 20ma @ 12 VDC, 22ma @ 24 VDC
- Minimum Start to Glow: 2.79 VDC
- Bi-directional polarity
- Available in Red, Blue, Green and Yellow
- Modern Illumination
- 6.3mm spade termination
- Fully encapsulated and vibration resistant
- No internal filament extending operating life and reducing downtime
- Cost effective replacement for standard pilot lights

Parts

- | | |
|--------------|---|
| ➤ APN: 2504 | 24V RESISTOR EXCITATION ASSEMBLY |
| ➤ APN: 8751 | 12V RESISTOR EXCITATION ASSEMBLY |
| ➤ APN: 11109 | LED PILOT LIGHT 6 - 32V 2 TERMINAL RED |
| ➤ APN: 11110 | LED PILOT LIGHT 6 - 32V 2 TERMINAL GREEN |
| ➤ APN: 11111 | LED PILOT LIGHT 6 - 32V 2 TERMINAL YELLOW |
| ➤ APN: 11112 | LED PILOT LIGHT 6 - 32V 2 TERMINAL BLUE |



Specifications

Thread diameter:	16mm
Fits hole diameter:	17-20mm
Spade terminal:	6.3mm
Fits panel thickness:	up to 20mm

Reference: SBAP0513060



RCT
Head Office
Unit 1-5/511 Abernethy Rd
Kewdale WA 6105, Australia
sales@rct-global.com

Australia +61 8 9353 6577
Africa +27 83 292 4246
Canada +1 705 590 4001
Central Asia +7 910 411 1174
USA +1 801 938 9214
South America +56 3 5229 9409

Copyright © 2023 Remote Control Technologies Pty Ltd. Images for illustration purposes only. Discover more @ rct-global.com