

Safe area warning on machine start

PRE-START WARNING CONTROLLERS

The Muirhead Pre-start Warning timers are designed to notify personnel within the vicinity of a machine that the engine is about to start. The system interfaces into the machine's starter circuit to provide a timed interlock; preventing the engine from immediately cranking when the ignition key is turned to the start position.

The system can be set to sound the machine's horn, alarm or any other type of electronic warning device or indicator.

The Muirhead Pre-start Warning timers are available with a variety of alarm configurations or can be custom-built to suit customer's needs.

The latest version of the Muirhead Pre-start Warning timer retains the simple, on machine time period adjustment and the ability for advanced setup and configuration on a PC through the Muirhead Programmable Controller Utility software package (PDU).



Caractéristiques

- Unité multi-tension 12-24 volts. Utilisation
- Universal application
- Easy-to-install and maintain
- Simple on machine time period adjustment
- Integrated mount
- Advanced configuration via the Muirhead® Programmable Controller Utility (PDU)

Specifications

| | |
|------------------------|---|
| System Voltage | 12 to 24 VDC (reverse polarity protected) |
| Maximum Current Output | 10Amp Continuous |
| Environmental Rating | IP 65 |
| Inputs | Digital / Analogue |
| Outputs | Digital |
| Operating Temperature | -10 to +65 °C |
| Dimensions | L- 199mm, W- 80mm, H- 65mm |

Pièces

- APN: 12539 PROGRAMMABLE PRE START WARNING
- APN: 12727 KIT PRE-START WARNING TIMER WITH 102DB ALARM
- APN: 12728 KIT PRE-START WARNING TIMER (NO ALARM)

Reference: SBMH0615123



RCT
Head Office
Unit 1-5/511 Abernethy Rd
Kewdale WA 6105, Australia
sales@rct-global.com

Australia +61 8 9353 6577
Africa +27 83 292 4246
Canada +1 705 590 4001
Central Asia +7 910 411 1174
USA +1 801 938 9214
South America +56 3 5229 9409

Copyright © 2023 Remote Control Technologies Pty Ltd. Images for illustration purposes only. Discover more @ rct-global.com